

## SanRex Corporation

50 Seaview Boulevard

Port Washington, NY 11050-4618

PH#516 625 1313 FX#516 625 8845

### Specification of Major Line up for Xenon Ballasts

New!!

	1000W	2000W	3000W	4000W	7000W
<b>Control Method</b>	Constant Current	Constant Current	Constant Power	Constant Current	Constant Current
<b>Rated Output Current</b>	53A (55AMax)	80A (85AMax)	100A (110AMax)	125A (138AMax)	180A (180AMax)
<b>Rated Output Voltage</b>	19V	25V	30V	32V	39V
<b>Rated Input</b>	Single Phase				Three Phase
	200-240V 50Hz / 60 Hz				200-208V/ 380-415V 50Hz-60Hz
<b>Approximate Size (Except Fan, Terminals and Ignitor) [mm]</b>	360(W)x250(D)x110(H)		290(W) x 420(D) x 177(H)	515(W) x 360(D) x 130(H) or 335(W) x 360(D) x 230(H)	500(W) x 330(D) x 355(H)
<b>Ignitor</b>	Separated Module				

Specifications are subject to change without any notice.

Contact us for additional information about SanRex's outstanding lamp ballasts.

<http://www.sanrex.com/>